
# PLUGS & SOCKETS

# PHONE PLUGS & SOCKETS

# PLUGS 2.5MM





# 2.5MM




Red

Stereo plug 2.5mm -Soft plastic handle -Plastic strain relief -4.2mm cable entry.


## 3.5MM

PS25.R




Mono plug 3.5mm - soft plastic handle - strain relief -4.5mm cable entry.

#### 3.5MM



Stereo plug 3.5mm - soft plastic handle - strain relief— 4.5mm cable entry.

## 3.5MM



3.5mm Plug - shielded metal handle - spring - 4.95mm cable entry.

#### 3.5MM

Stereo right angle plug 3.5mm - soft plastic handle -strain relief 4.5mm cable entry.

Part Number PS35RA



Part Number	Type
P65.B	Black
P65 R	Red

Mono plug 6.35mm - soft plastic handle—strain relief - 6.0mm cable entry.

# 6.35M





Mono 6.35mm extra heavy duty musical instrument plug. Metal body in PVC boot with flexible cable entry. Solder terminating.



Part Number	Style
P65M	Round Tip
P65MPT	Point Tip

Mono plug 6.35mm - Round/ Point tip, metal handle -spring - 6.5mm entry.

#### 6.35M

Narrow body right angle mono plug 6.35mm shielded-metal handle 2.0mm cable





# 6.35MM



Part Number	Type	Stereo plug 6.35mm - soft
PS65.B	Black	plastic handle - strain relief
PS65.R	Red	6.00mm cable entry.

#### 6.35MM



Part Number PS65M

Stereo plug 6.35mm - shielded metal handle and spring - 6.5mm cable entry.

#### SOCKETS 2.5MM

Mono 2.5mm chassis socket open circuit -Nut mounting.



Mono 2.5mm chassis socket closed circuit -closed housing



Stereo 2.5mm chassis socket open circuit -closed housing



Stereo 2.5mm PCB mount socket - switched



Mono 3.5mm chassis socket open circuit - nut mounting




Mono 3.5mm chassis socket closed circuit -Closed housing



Stereo 3.5mm chassis socket open circuit - closed housing



Mono 3.5mm PCB socket SPST Switched




Stereo 3.5mm Chassis socket DPST Switched



Part Number

P0094

Stereo 3.5mm PCB socket DPST Switched



Stereo 3.5mm PCB socket switched



SEMTRONICS P/L

JS35PC



Mono 6.35mm chassis socket switched -Nut mounting



Mono 6.35mm PCB mount socket - switched. Nut mounting



Stereo 6.35mm chassis socket closed circuit-Nut mounting



Stereo 6.35mm chassis socket switched -Nut mounting



Stereo 6.35mm PCB mount socket - switched, Nut mounting




Stereo 6.35mm chassis mount socket-closed Circuit. Nut mounting

P0072

# INLINE SOCKETS

# 2.5MM





.5mm Inline socket plastic handle strain relief -4.2mm cable entry

### 3.5MM

U



Part Number	Type	Style	3.5mm
F\$35B	Black	Mono	Inline soc
F\$35R	Red	Mono	plastic ha strain reli
FSS35B	Black	Stereo	4.2mm ca
FSS35R	Red	Stereo	

## 6.35MM



Part Number	Type	Style	Inline sock
FS65B	Black	Mono	Plastic/shie
FSS65B	Black	Stereo	metal hand spring -
FSS65M	Metal	Stereo	6.0mm cab

# Part Number

Mono 6.35mm chassis socket closed circuit—nut mounting



































	Red	Mono	strain relief -	
	Black	Stereo	4.2mm cable entry	
	Red	Stereo		